


## Battery Bank Combiner



PathMaker 100



Pathmaker 250

### Multiple Battery Bank Charging

PathMaker is a battery combiner that automatically connects two or three battery banks for simultaneous charging and isolates them during discharge. A toggle switch allows the user to manually parallel battery banks for emergency starting power. For use with 12 or 24-volt systems, PathMaker has user adjustable settings for connect and disconnect.

### Product Features

- ▶ Automatic, high current switch for simultaneous two to three bank charging
- ▶ Connects batteries together when the voltage is sufficiently high and disconnects when voltage drops during discharge
- ▶ No voltage drop in charging voltage
- ▶ Manual connect feature for emergency starts
- ▶ Compatible with all DC charging sources
- ▶ Convenient front panel LED status indicators
- ▶ User-selectable connect and disconnect voltages
- ▶ Optional Remote Control - indicates Off, Auto and Combine
- ▶ One year warranty

### Options

- ▶ Four models available
- ▶ Available in two or three battery bank versions with models at 100 and 250 Amps

### Xantrex Technology Inc.

Headquarters  
8999 Nelson Way  
Burnaby, British Columbia  
Canada V5A 4B5  
800 670 0707 Toll Free  
604 420 1591 Fax

5916 195 Street NE  
Arlington, Washington  
USA 98223  
800 446 6180 Toll Free  
360 925 5144 Fax

## Battery Bank Combiner

### Specifications

<b>Current ratings</b>	100 A: 100 A continuous, 400 A peak
	250 A: 250 A continuous, 2000 A peak
<b>Voltage range</b>	7 – 33 V (24 V assumed if > 18.0 V)
<b>Low voltage disconnect range</b>	12.8 – 13.2 V (X2 for 24 V)
<b>Connect voltage range</b>	13.1 – 13.5 V (X2 for 24 V)
<b>High voltage disconnect range</b>	14 – 16 V (X2 for 24 V)
<b>Idle power consumed</b>	0.40 W @ 12 V, 0.54 – 1.0 W @24 V
<b>Connected power</b>	100 A/2 Bank 7.74 W @12 V, 10.78 W @ 24 V
	100 A/3 Bank 13.2 W @12 V, 17.4 W @ 24 V
	250 A/2 Bank 2.24 W @12 V, 3.69 W @ 24 V
	250 A/3 Bank 3.46 W @12 V, 5.43 W @ 24 V
<b>Indicator lights</b>	Disabled: Yellow
	Connected: Green
	High Voltage Disconnect: Red
	Wait for Reconnect: Flashing Red
<b>External control</b>	User supplied momentary on/off switch
<b>Operating temperature range</b>	-40 – 65°C
<b>Remote panel (optional)</b>	Flush mount, splashproof front, 25' cable included
<b>Dimensions (HxWxD)</b>	100 A: 6.3 x 7.4 x 3.6"
	250 A: 7.6 x 7.4 x 3.2"
<b>Warranty</b>	One year
<b>Weight</b>	100 A/2 Bank: 1.3 lbs.
	100 A/3 Bank: 1.7 lbs.
	250 A/2 Bank: 1.9 lbs.
	250 A/3 Bank: 2.9 lbs.
<b>Part Numbers</b>	84-2051-02 (100 A with 2 battery banks)
	84-2051-03 (100 A with 3 battery banks)
	84-2094-01 (250 A with 2 battery banks)
	84-2094-03 (250 A with 3 battery banks)
	84-2053-00 (Remote with 25' cable)

Note: Specifications subject to change without notice.